SSD Firmware Update Instructions

Before updating the firmware on the SSD we recommend backing up all of the data that is on the drive.

The update process requires Administrator rights. The drive will not be detected if administrator privileges are not enabled.

To start the update process, double click ssdupdate.exe

50 Update Firmware Package File				
rive List Model Serial Number Firmw	are Rev Capacity			
Download Firmware to Selected Drive	Refresh Drive List			
drives found!	O CEILLEY	No Drives foun	d! (No administrat	or ri

 	File			Firmware Packa	ge File		
rive List				Drive List			
Model	Serial Number	Firmware Rev	Capacity	Model	Serial Number	Firmware Rev	Capacity
SandForce	000000	300A12F0	64GB	SandForc	e 000000	300A12F0	64GB
Download Firmwar	re to Selected Drive	Re	fresh Drive List	Download Firm	ware to Selected Drive	Re	fresh Drive List

Drive found, the drive to be updated must be checked. Only one drive should be selected at a time. Be sure to close all applications prior to updating the firmware.

Once the target drive has been selected and the select the Firmware Package File (3.4.6.pkg).

The update is initiated by clicking "Download Firmware to Selected Drive."

SSDUPDATE		
♪	Make sure to backup your data before upgrading firmware. Your system will reboot automatically. Proceed with firmware upgrade?	
	OK Cancel	

A pop-up will be displayed to advise the user to back-up data and indicate that the system will be restarted. This pop-up offers a cancel option that aborts the update.

NOTE: Although the system is rebooted automatically, the system must be <u>shut down</u> and restarted following the firmware update. If the system is not shut down and restarted, the drive will not be detected on some systems.